



Power board COB1605

Power board for extractor hoods and management of motor, lights and accessories. Motor management sequential 3/4 speed (multi-winding) or brushless with PWM management and On-Off lights control maximum 1200W. It is possible to add a 433MHz Rx module for radio frequency and duct opening control, free contacts or management of additional duct motorisation. The board complies with the latest Energy Label and Ecodesign standards. Standby consumption is less than 0.5W and it is possible to plug in a Cobofra Wi-Fi module for control via apps, Alexa and Google Home.

| | |
|---------------------|-------------------------------|
| Board technology | Relay |
| Motor output | 220-240VAC 50-60Hz - Max 600W |
| Output 3 | / |
| Micro contact 1 | Optional |
| Standby consumption | < 0,5W |
| BT/Wi-Fi Technology | Optional |
| Product size | 100x57 mm |

| | |
|---------------------------|--------------------------------|
| Input voltage | 220-240VAC 50-60Hz |
| Light output | 220-240VAC 50-60Hz - Max 1200W |
| Output 4 | / |
| Micro contact 2 | Optional |
| Remote control technology | 433MHz - Optional |
| Operating temperature | 0° +60° |
| Conformity | CE/Energy Label/Ecodesign |

Field of application:

Professional extractor hoods

Extractor hoods

Via Enrico Fermi 10 – Z.I. – 35020 LEGNARO (PD) – tel 049 790876 Fax 049 790993
C.F/P.IVA 00388610289
Numero REA 251745
cobofra@cobofra.com

-ELECTRONIC CONTROLS

-INVERTER

-CABLING

-LIGHTING SOLUTIONS

